

BW-CAM-NANO19

3G-SDI OSD MANUAL

SETUP MENU	SUB MENU1	SUB MENU2	SUB MENU3	VALUE			
LENS	DC			INDOOR/ OUTDOOR/ DEBLUR			
	MANUAL			NORMAL/ DEBLUR			
EXPOSURE	BRIGHTNESS			0 ~ 20			
	AGC			0 ~ 20			
	SHUTTER MODE			AUTO/ MANUAL/ FLICKERLESS			
	SHUTTER SPEED			1/30(25),60(50),120(100),250,700,1K,1.6K,2.5K,5K,7K,10K,30K			
	SENS-UP			OFF/ X2/ X4/ X8 / X16 / X32			
WHITE BALANCE	AWB						
	ATW						
	PUSH LOCK			Press ENTER key			
	MANUAL	COLOR TEMP.			3000K/ 5000K/ 8000K		
		R-GAIN			0 ~ 20		
	B-GAIN			0 ~ 20			
BACKLIGHT	OFF						
	HLC	LEVEL			0 ~ 20		
		COLOR			BLK,WHT,YEL,CYN,GRN,MAG,RED,BLU		
	BLC	H-POS			0 ~ 20		
		V-POS			0 ~ 20		
		H-SIZE			0 ~ 20		
		V-SIZE			0 ~ 20		
	WDR	WEIGHT			LOW/ MIDDLE/ HIGH		
DNR				OFF/ LOW/ MIDDLE/ HIGH			
DAY&NIGHT	AUTO	DWELL TIME			0 ~ 9sec, 1sec/ step		
		AGC THRES			0(bright) ~ 20(dark)		
		AGC MARGIN			0(bright) ~ 20(dark)		
	COLOR						
	B&W						
IMAGE	SHARPNESS				0 ~ 20		
	COLOR LEVEL				0 ~ 20		
	MIRROR				OFF/ ON		
	FLIP				OFF/ ON		
	LENS SHADING	OFF/ ON			WEIGHT 0~100%		
	GAMMA				0.45/ 0.55/ 0.65/ 0.75		
	D-ZOOM				1~16X		
	ACE				OFF/ LOW/ MIDDLE/ HIGH		
	DEFOG	AUTO/MANUAL			LOW/ MIDDLE/ HIGH		
SPECIAL	PRIVACY	BOX			OFF		
						MASK SEL	0 ~ 15
						MASK MODE	OFF/ ON
						H-POS	0 ~ 60
						V-POS	0 ~ 34
						H-SIZE	0 ~ 40
						V-SIZE	0 ~ 34
						Y LEVEL	0 ~ 20
						CB LEVEL	0 ~ 20
						CR LEVEL	0 ~ 20
				TRANS	0 ~ 3		
		POLYGON				OFF	
						MASK SEL	0 ~ 7
						MASK MODE	OFF/ ON
						POS0-X - POS3-X	0 ~ 120
						POS0-Y - POS3-Y	0 ~ 68
						Y LEVEL	0 ~ 20
						CB LEVEL	0 ~ 20
						CR LEVEL	0 ~ 20
						TRANS	0 ~ 3

SETUP MENU	SUB MENU1	SUB MENU2	SUB MENU3	VALUE
SPECIAL	MOTION	OFF		
		DET WINDOW	WINDOW SEL	0 ~ 3
			WINDOW MODE	OFF/ ON
			DET H-POS	0 ~ 60
			DET V-POS	0 ~ 34
			DET H-SIZE	0 ~ 60
			DET V-SIZE	0 ~ 34
		SENSITIVITY	0 ~ 10	
		MOTION OSD	OFF / ON	
		TEXT ALARM	OFF/ ON	
		ESTIMATE	OFF/ ON	
		QUICK ZOOM	OFF	
	ZOOM SPEED		LOW/ MIDDLE/ HIGH	
	TRACKING		OFF/ ON	
	REPEAT		OFF/ ON	
	DIS	OFF		
		RANGE	10%/ 20%/ 30%	
FILTER		LOW/ MIDDLE/ HIGH		
AUTO C		OFF/ HALF/ FULL		
SYSTEM	SDI OUT		HD-SDI/ EX-SDI	
	SDI FORMAT		1080_30p/ 1080_25p/ 1080_60p/ 1080_50p/ 720_30p/ 720_25p/ 720_60p/ 720_50p/ 1080_60i/ 1080_50i	
	FREQ(NT/PAL)		60Hz(NTSC)/ 50Hz(PAL)	
	CVBS OUT		OFF/ ON	
	LANGUAGE		ENG/ CHINESE/ CHINESE(S)/ JAPANESE/ KOR	
	CAM TITLE		0 ~ 9, A ~ Z, blank	
FACTORY DEFAULT			Reset to factory setting	
RETURN			Return to previous menu	
EXIT			Exit SETUP menu	

WDR is not operated when 'SHUTTER MODE=MANUAL'

WDR mode is OFF when CVBS ON.

Left + Left + Left + Enter : EX-SDI

Right + Right + Right + Enter : HD-SDI

